

## REMARKS

This Preliminary Amendment cancels the original claims, without prejudice, in the underlying PCT Application No. PCT/DE2004/001482. The Preliminary Amendment also adds new claims 6-10. The new claims conform the claims to U.S. Patent and Trademark Office rules and do not add new matter to the application.

In accordance with 37 C.F.R. § 1.125(b), the Substitute Specification (including the Abstract) contains no new matter. The amendments reflected in the Substitute Specification (including Abstract) are to conform the Specification and Abstract to United States Patent and Trademark Office rules or to correct informalities. As required by 37 C.F.R. §§ 1.121(b)(3)(ii) and 1.125(c), a Marked-Up Version of the Substitute Specification comparing the Specification of record and the Substitute Specification also accompanies this Preliminary Amendment. Approval and entry of the Substitute Specification (including Abstract) are respectfully requested.

The underlying PCT Application No. PCT/DE2004/001482 includes an International Search Report, dated October 20, 2004, a copy of which is submitted herewith.

Applicants assert that the subject matter of the present application is new, non-obvious, and useful. Prompt consideration and allowance of the application are respectfully requested.

Respectfully submitted,

KENYON & KENYON

*2,172 (S.No. 4,172)*

Dated: \_\_\_\_\_

*1/25/06*

By: \_\_\_\_\_

*GC*

Gerard A. Messina  
Reg. No. 35,952

One Broadway  
New York, NY 10004  
(212) 425-7200

# METHOD FOR DIGITAL DATA TRANSMISSION FROM A SENSOR TO A CONTROL UNIT

## ~~Background Information~~ Field Of The Invention

The present invention is directed to a method for digital data transmission from a sensor to a control unit ~~according to the definition of the species in the independent patent claim.~~

## Background Information

5 A method for digital data transmission from a sensor to a control unit is known from  
~~DE~~ German Published Patent Application No. 102 29 945 A1-945. A pressure sensor signal is  
divided into a direct component and a differential pressure component, the direct component  
being transmitted from the sensor to the control unit at a lower resolution than the differential  
pressure component.

## 10 ~~Advantages of the~~ Summary Of The Invention

The method according to the present invention for digital data transmission from a sensor to a  
control unit ~~having the features of the independent patent claim~~ has the advantage over the  
related art that a linear range of values including successive sensor values is formed and an  
additional range of values which is transmitted from the sensor to the control unit at a higher  
15 resolution is cut out of it as a function of a variable relevant for the control unit. This means that  
the two divided ranges of values are sub-ranges of the total range of values. The two ranges of  
values are successive in particular. This makes it possible, as a function of the variable relevant  
for the control unit, to select the range of values which the control unit preferably needs for its  
analysis. This saves bandwidth, since only the important values are transmitted at a high  
20 resolution, and a high resolution is still allowed for these important values.

~~The measures and refinements listed in the dependent claims make advantageous  
improvements on the method for digital data transmission from a sensor to a control unit  
recited in the independent patent claim possible.~~

25 It is particularly advantageous that the variable, as the function of which the range of values  
transmitted from the sensor to the control unit at a high resolution is selected, indicates the  
range of values within which the threshold values of an algorithm for a restraining means lie.  
This range of values is already predefined, this range of values being determined via  
simulations. Values which lie below or above may be transmitted at a lower resolution since an

unambiguous decision must be reached with respect to triggering. The values, which lie very close to the general threshold values, are important for reaching an accurate triggering decision. If bidirectional transmission is provided from the control unit and the sensor, it may be the case that the control unit transmits such variables to the sensor. However, unidirectional  
5 transmission from the sensor to the control unit is generally provided, the sensor, which may be an external pressure sensor, an acceleration sensor, a weight sensor, or a pre-crash sensor, being able to be additionally supplied with power from the control unit via the line, and the sensor impressing its data on this power supply via a current modulation, for example.

10 The range of values which is transmitted at a higher resolution is advantageously situated in the lower half of the total range of values of the sensor values. Very high sensor values result in an unambiguous decision in a triggering algorithm of a control unit, while lower values require a more specific check to be able to execute a proper and accurate decision for triggering restraining means, such as airbags or seat-belt tensioners.

15 The method according to the present invention may advantageously also be used for a vehicle dynamics control system, roll-over detection and ESP (electronic stability program), for example.

#### Drawing

~~Exemplary embodiments of the present invention are illustrated in the drawing and explained in greater detail in the following description.~~

#### Brief Description Of The Drawings

~~Fig. 1~~ Fig. 1 shows a data transmission between the sensor and the control unit,

~~Fig. 2~~ Fig. 2 shows a division of the range of values, and

~~Fig. 3~~ Fig. 3 shows a flow chart of the method according to the present invention.

#### Detailed Description of the Exemplary Embodiments

25 Crash sensors have a linear or other type of characteristic curve with which crash signals are detected. External crash sensors transmit this data in coding to an airbag control unit. The measuring range is linearly mapped on the individual digital transmission values.

The fact that the measuring range is linearly distributed on the individual admissible transmission values results in a fixed, constant resolution across the entire measuring range.

30 However, this is disadvantageous since certain ranges of values having a higher resolution than

others should be available for analysis. In a pressure sensor, the range, for example, in which the separation between triggering and non-triggering takes place, is of greater interest than the pressure characteristics which clearly lie above the triggering threshold anyway. Such triggering thresholds may be fixed or may be adaptively changed, i.e., they are adaptively  
5 changed as a function of the crash-characterizing values. The change is then maintained for a certain amount of time in order to be changed again as applicable as a function of the crash characteristics. It is frequently not possible to transmit the entire range of values at a higher resolution for economic reasons.

The range of values of a sensor is divided into different ranges in which the values are linearly  
10 redistributed on the existing triggering values. However in the case of a pressure sensor, for example, the measuring range is divided into two even halves, for example. The first half having the lower pressure signals is distributed on  $\frac{3}{4}$  of the possible transmission values, while the second half having the higher pressure signals is linearly distributed on the remaining  $\frac{1}{4}$  of the possible transmission values. This results in the lower pressure values having a higher  
15 resolution, while the high pressure values are transmitted at a lower resolution.

The values in the range are distributed in a different and adapted manner in certain intervals depending on the sensor and the accuracy requirement. This distribution may be implemented via the interface, i.e., the transmitter module of the sensor. In the case of pressure values, for example, the bit width of the data transmission may be reduced at least from 16 bits to 8 bits,  
20 which makes substantial cost savings and data reduction possible.

Additional application examples for this method are, for example, up-front sensors, peripheral acceleration sensors, and acceleration sensors in the control unit. Due to the higher resolution of the signals of the up-front sensor at lower accelerations, they may also be used for pedestrian protection, for plausibility with other sensors, contact sensors, for example. A truck underride  
25 may also be better detected in this manner.

In the case of peripheral acceleration sensors and the sensors in the control unit, the plausibility and the crash onset may be determined more accurately due to a better resolution in small signals. The sensors may then also be used for determining vehicle-dynamic variables, i.e., for roll-over sensing and ESP. Determining the mounting direction for checking the installation  
30 direction is thereby also made easier. The method according to the present invention is also advantageous here, since the pre-crash sensor generates a great data flow.

Figure 1 shows a block diagram of the transmission from a sensor to a control unit. A pressure sensor PPS is shown here as the sensor having a sensor element 10 including downstream electronics and a transmitter module 11 for transmitting the sensor values. The sensor values are transmitted to transmitter module 11 by the sensor element. Transmitter module 11  
5 executes the division of the sensor values according to the present invention as a function of a variable relevant for the control unit. As an example, the range of values, in which the threshold values for analyzing the pressure signal lie, is transmitted at a higher resolution. Rougher divisions are also possible, e.g., only the lower half of the pressure sensor values is transmitted at a higher resolution. The transmitted sensor values are subsequently received by a receiver  
10 module 12 in control unit SG. The resolution of the sensor values is reversed here, i.e., the resolved sensor values are mapped again on the original sensor values which are subsequently analyzed in a processor 13 of control unit SG. The analysis takes place in a triggering algorithm in order to activate connected restraining means (not shown) in the event of deployment.

Instead of a pressure sensor PPS, it is alternatively possible to use the method according to the  
15 present invention in peripheral acceleration sensors in the side section or in the front-end section of the vehicle or also sensors in the control unit itself. Instead of a control unit for restraining means as shown here, control units for a vehicle dynamics control system are also possible. A kinematic sensor platform may also use the method according to the present invention for transmitting its sensor values.

Figure 2 explains in an illustration the distribution of the sensor values on the transmission  
20 values. Sensor values from 0 to 200 may be generated in sensor element 10, as illustrated in first section 20. However, the threshold values in control unit SG lie in range 22 which ranges from 0 to 50, i.e., the other range 23 from 50 to 200 is not so interesting since this range results in an unambiguous resolution because these values are well above the threshold values.  
25 Therefore, range 22 is transmitted at a higher resolution. This takes place via mapping on possible transmission values 21. Transmission values 21 are 8 bits here, from 0 to 255. In first range 24 of the transmission values, which ranges from 0 to 180, the values from range 22 are linearly mapped and are thus transmitted at a higher resolution. Range 23 is mapped on range of values 24 and is thus transmitted to control unit SG at a lower resolution. The corresponding  
30 resolution may be signaled in the data message from sensor PPS to control unit SG.

Figure 3 uses a flow chart to explain the procedure of the method according to the present invention. The sensor values are generated by sensor element 10 in method step 300 and are

amplified, digitized, and filtered in the associated electronics. The sensor values, digitized in this way, are subsequently supplied to transmitter module 11 which divides the sensor values according to the present invention in method step 301. Transmitter module 301 executes the division of the sensor values as a function of the variable relevant for the control unit, the possible threshold values for the triggering algorithm in this case. Transmitter module 11 selects the range of values, in which the threshold values may appear, for transmission at a higher resolution, while it transmits the outlying range of values at a lower resolution. The sensor values, divided in this way, are transmitted in method step 302. In method step 303, the sensor values are received by control unit SG via receiver module 12 and supplied to processor 13 for processing in the triggering algorithm.

According to Figure 2, a sensor value 48 which lies in range 22 is generated as an example. Therefore, this measured value 48 is transmitted from range 24 at a higher resolution. Transmission values 168 to 171 are then used for this measured value 48 as an example.

Abstract Of The Disclosure

A method for digital data transmission from a sensor (~~PPS~~) to a control unit (~~SG~~) is described, the sensor values of the sensor (~~PPS~~) being divided for data transmission at different resolutions. The sensor values form a first range of values including successive sensor values. The first range of values for data transmission is divided as a function of a variable relevant for the control unit (~~SG~~).

(Figure 1)